

HUDSON & HUDSON NEON, INC.

LUMINOUS TUBE FOOTAGE CHART

APPROXIMATE FOOTAGE OF TUBING OPERATED

**WHEN DETERMINING TUBE LENGTH PLEASE ADD 1 FT PER UNIT

281.999.3434 WWW.HUDNEON.COM

TUBES FILLED WITH RED(Ne) GAS

TUBES FILLED WITH BLUE(Ar) GAS

high pwr factor	noremal pwr factor	SECONDARY VOLTAGE	MILLIAMPERAGE RATING	25MM	22MM	20MM	18MM	15MM	14MM	13MM	12MM	11MM	10MM	9MM	25MM	22MM	20MM	18MM	15MM	14MM	13MM	12MM	11MM	10MM	9MM	SECONDARY VOLTAGE
464	900	15,000V	60MA	102	85	78	72	60	54	50	45	40	36	32	120	100	90	80	72	64	60	54	48	44	39	15,000V
232	450		30MA	102	85	78	72	60	54	50	45	40	36	32	120	100	90	80	72	64	60	54	48	44	39	
371	720	12000V	60MA	79	67	61	55	44	42	39	35	32	29	26	95	79	70	62	55	50	46	42	38	35	31	12000V
185	360		30MA	79	67	61	55	44	42	39	35	32	29	26	95	79	70	62	55	50	46	42	38	35	31	
556	1080	9000V	120MA	77	65	55	46	38	34	33	30	26	23	20	92	77	63	52	46	41	38	35	31	27	24	9000V
278	540		60MA	67	57	48	40	33	30	29	26	24	21	18	80	67	55	45	40	36	33	31	28	25	22	
139	270		30MA	67	57	48	40	33	30	29	26	24	21	18	80	67	55	45	40	36	33	31	28	25	22	
93	180		20MA					28	26	24	22	22	19	18	16					34	31	29	26	23	20	
464	900	7500V	120MA	59	47	39	34	29	27	26	23	21	19	17	70	55	45	39	35	32	31	27	25	22	19	7500V
232	450		60MA	51	41	34	28	26	24	22	21	19	17	15	61	48	39	35	31	28	27	25	23	20	18	
116	225		30MA	51	41	34	28	26	24	22	21	19	17	15	61	48	39	35	31	28	27	25	23	20	18	
77	150		20MA					22	21	20	18	16	15	13					27	25	24	21	19	18	16	
371	720	6000V	120MA	46	39	32	27	23	22	21	19	17	15	13	55	46	37	32	27	26	25	23	20	18	16	6000V
185	360		60MA	40	34	28	23	20	19	18	16	15	13	12	48	40	32	28	24	23	21	19	18	16	14	
93	180		30MA	40	34	28	23	20	19	18	16	15	13	12	48	40	32	28	24	23	21	19	18	16	14	
62	120		20MA					18	17	16	14	13	11	10					22	20	18	17	15	13	12	
309	600	5000V	120MA	38	32	26	22	19	18	17	14	12	11	9	46	38	31	26	23	22	19	18	15	13	11	5000V
155	300		60MA	33	28	23	19	17	16	15	12	11	10	8	40	33	27	23	20	19	16	15	13	12	10	
77	150		30MA	33	28	23	19	17	16	15	12	11	10		40	33	27	23	20	19	16	15	13	12	10	
52	100		20MA					15	13	13	11	9	8	7					18	16	15	13	12	11	9	
124	240	4000V	60MA	27	23	19	16	13	12	11	10	9	8	7	32	27	22	19	16	14	13	12	10	9	8	4000V
62	120		30MA	27	23	19	16	13	12	11	10	9	8	7	32	27	22	19	16	14	13	12	10	9	8	
41	80		20MA					11	10	10	9	8	7	6					13	12	12	11	9	8	7	
93	180	3000V	60MA	17	14	12	11	10	9	9	8	7	6	5	22	18	16	14	12	11	10	9	8	7	6	3000V
46	90		30MA	17	14	12	11	10	9	9	8	7	6	5	22	18	16	14	12	11	10	9	8	7	6	
31	60	2000V	20MA					8	8	7	6	5	4	4					10	9	8	7	6	5	5	2000V
31	60		30MA					7	6	6	6	5	4	4					9	8	8	7	6	5	5	
21	40		20MA					6	5	5	5	4	3	3					7	7	7	6	5	4	4	